

FSP2161

FEATURES

- Low-Dropout Regulator Supports Input Voltages Down to 1.4V
- Output Voltage Available in 0.9V, 1.0V, 1.2V, 1.5V, 1.8V, 2.5V, 2.8V, 2.85V, 3.0V, 3.3V
- Stable with a Ceramic Output Capacitor of 1.0uF or Higher
- Low Dropout Voltage: 150mV at 1.5A
- Low Quiescent Current
- Over Temperature Shutdown
- Short Circuit Protection
- Low Temperature Coefficient
- Standard TO252 and TO263 Packages


APPLICATIONS

- DSP, FPGA, and Microprocessor Power Supplies
- 1.2V Core Voltage for DSPs
- SATA Power Supply
- LCD TV/ Monitors
- Wireless Devices
- Communication Devices
- Portable Electronics
- Post Regulator for SMPS

PIN CONFIGURATION


1) TO252

(Top View)



2) TO263



(Top View)





PIN DESCRIPTION

| Pin Number | | Pin Name | Pin Function |
|------------|-------|----------|--------------|
| TO252 | TO263 | | |
| 1 | 1 | VIN | Input |
| 2 | 3 | GND | Ground |
| 3 | 5 | VOU | Output |
| | 2 | EN | Enable pin |
| | 4 | PWRGD | Power good |

BLOCK DIAGRAM



■ TYPICAL APPLICATIONS CIRCUITS



■ ABSOLUTE MAXIMUM RATINGS

| Parameter | Rating | Unit |
|--|-----------------|------|
| Input Supply Voltage | +4 | V |
| Maximum Output Current | PD/(VIN-VO) | |
| Output Pin Voltage | -0.3 to VIN+0.3 | V |
| Internal Power Dissipation | 1200 | mW |
| Junction to Case Thermal Resistance (θ_{JC}) | 7 | °C/W |
| Junction to Ambient Thermal Resistance (θ_{JA}) | 90 | °C/W |
| Operating temperature | -40 to 85 | °C |
| Operating Junction Temperature | -40 to 125 | °C |
| Storage Temperature | -65 to 150 | °C |
| Maximum Junction Temperature | 150 | °C |
| Lead Temperature (Soldering, 5 sec) | 300 | °C |

Note: These are stress ratings only and functional operation is not implied. Exposure to absolute maximum ratings for prolonged time periods may affect device reliability. All voltages are with respect to ground.

■ RECOMMENDED OPERATING CONDITIONS

| Parameter | Rating | Unit |
|--------------------------------|------------|------|
| Input Supply Voltage | 1.4 to 3.6 | V |
| Operating temperature | -40 to 85 | °C |
| Operating Junction Temperature | -40 to 125 | °C |

■ ELECTRICAL CHARACTERISTICS

($V_{OUT} = V_{IN} + 0.5V$, $C_{IN} = 1\mu F$, $C_O = 2.2\mu F$, $T_A = 25^\circ C$ unless otherwise specified.)

| PARAMETER | SYMBOL | TEST CONDITIONS | | MIN | TYP | MAX | UNIT |
|-------------------------------|------------|---|------------------------|-------|-----|-----|------------------|
| Input Voltage | V_{IN} | | | Note1 | | 3.6 | V |
| Output Voltage Accuracy | V_O | $I_O = 100mA$ | | -2 | | +2 | % |
| Short Circuit Current | I_{SC} | $V_O < 0.3V$ | | | 1.0 | | A |
| Ground Current | I_{GND} | $I_O = 1mA$ to $1.5A$ | | | | 600 | μA |
| Quiescent Current | I_Q | $I_O = 0mA$ | | | 90 | 150 | μA |
| Line Regulation | LNR | $I_O = 10mA$, $V_O \leq 2.5V$ $V_{IN} = V_O + 0.5V$ to $V_O + 1.5V$ | | | 0.5 | 1 | % / V |
| | | $I_O = 10mA$, $V_O > 2.5V$ $V_{IN} = 3.3V$ to $3.6V$ | | | 0.5 | 1 | |
| Load Regulation Error | LDR | $I_O = 1mA$ to $1.5A$ | | | 0.5 | 2 | % / A |
| Temperature Coefficient | T_C | | | | 40 | | ppm / $^\circ C$ |
| Over Temperature Shutdown | OTS | | | | 150 | | $^\circ C$ |
| Over Temperature Hysteresis | OTH | | | | 50 | | $^\circ C$ |
| Power Supply Ripple Rejection | PSRR | $I_O = 100mA$ $V_O = 1.5V$ | $f = 100Hz$ | | 55 | | dB |
| | | | $f = 1KHz$ | | 55 | | |
| | | | $f = 10KHz$ | | 35 | | |
| Dropout Voltage | V_{DROP} | $I_O = 500mA$ | $V_O = 0.9V$ | | 330 | 500 | mV |
| | | | $V_O = 1.0V$ | | 220 | 400 | |
| | | | $1.2V \leq V_O < 2.5V$ | | 50 | 200 | |
| | | | $V_O \geq 2.5V$ | | 40 | 150 | |
| | | $I_O = 1.5A$ | $V_O = 0.9V$ | | 330 | 500 | |
| | | | $V_O = 1.0V$ | | 220 | 400 | |
| | | | $1.2V \leq V_O < 2.5V$ | | 150 | 350 | |
| | | | $V_O \geq 2.5V$ | | 120 | 300 | |
| Output Noise | V_n | $f = 10Hz$ to $100kHz$ | | | 40 | | μV_{RMS} |

Note 1: The minimum input voltage of the FSP2161 is determined by output voltage and dropout voltage. The minimum input voltage is defined as:

$$V_{IN(MIN)} = V_O + V_{DROP}$$

■ APPLICATION INFORMATION

The FSP2161 family of low-dropout (LDO) regulators have several features that allow them to apply to a wide range of applications. The family operates with very low input voltage (1.4V) and low dropout voltage (typically 150mV at full load), making it an efficient stand-alone power supply or post regulator for battery or switch mode power supplies. The 1.5A output current make the FSP2161 family suitable for powering many microprocessors and FPGA supplies. The FSP2161 family also has low output noise (typically 40μVRMS with 2.2μF output capacitor), making it ideal for use in telecom equipment.

External Capacitor Requirements

A 2.2μF or larger ceramic input bypass capacitor, connected between VIN and GND and located close to the FSP2161, is required for stability. A 1.0μF minimum value capacitor from VO to GND is also required. To improve transient response, noise rejection, and ripple rejection, an additional 10μF or larger, low ESR capacitor is recommended at the output. A higher-value, low ESR output capacitor may be necessary if large, fast-rise-time load transients are anticipated and the device is located several inches from the power source, especially if the minimum input voltage of 1.4 V is used.

Regulator Protection

The FSP2161 features internal current limiting, thermal protection and short circuit protection. During normal operation, the FSP2161 limits output current to about 3A. When current limiting engages, the output voltage scales back linearly until the over current condition ends. While current limiting is designed to prevent gross device failure, care should be taken not to exceed the power dissipation ratings of the package. If the temperature of the device exceeds 150°C, thermal-protection circuitry will shut down. Once the device has cooled down to approximately 50°C below the high temp trip point, regulator operation resumes. The short circuit current of the FSP2161 is about 1A when its output pin is shorted to ground.

Thermal Information

The amount of heat that an LDO linear regulator generates is:

$$P_D = (V_{IN} - V_O) I_O$$

All integrated circuits have a maximum allowable junction temperature ($T_{J\max}$) above which normal operation is not assured. A system designer must design the operating environment so that the operating junction temperature (T_J) does not exceed the maximum junction temperature ($T_{J\max}$). The two main environmental variables that a designer can use to improve thermal performance are air flow and external heatsinks. The purpose of this information is to aid the designer in determining the proper operating environment for a linear regulator that is operating at a specific power level.

In general, the maximum expected power ($P_{D(max)}$) consumed by a linear regulator is computed as:

$$P_{DMAX} = (V_{I(avg)} - V_{O(avg)}) I_{O(avg)} + I_{Q} I_{Q} (Q)$$

Where:

$V_{I(avg)}$ is the average input voltage.

$V_{O(avg)}$ is the average output voltage.







$I_{O(avg)}$ is the average output current.

I_Q is the quiescent current.

For most LDO regulators, the quiescent current is insignificant compared to the average output current; therefore, the term $V_{I(avg)} \times I_Q$ can be neglected. The operating junction temperature is computed by adding the ambient temperature (T_A) and the increase in temperature due to the regulator's power dissipation. The temperature rise is computed by multiplying the maximum expected power dissipation by the sum of the thermal resistances between the junction and the case ($R_{\theta JC}$), the case to heatsink ($R_{\theta CS}$), and the heatsink to ambient ($R_{\theta SA}$). Thermal resistances are measures of how effectively an object dissipates heat. Typically, the larger the device, the more surface area available for power dissipation so that the object's thermal resistance will be lower.


■ TYPICAL PERFORMANCE CHARACTERISTICS

1. Output Voltage vs Input Voltage








TYPICAL PERFORMANCE CHARACTERISTICS (CONTINUED)

2. Output Voltage vs Output Current




3. Output Voltage vs Temperature




■ TYPICAL PERFORMANCE CHARACTERISTICS (CONTINUED)


4. Quiescent Current vs Input Voltage




5. Quiescent Current vs Temperature




6. Ground Current vs Output Current



7. Ground Current vs Input Voltage




8. Dropout Voltage vs Output Current




■ TYPICAL PERFORMANCE CHARACTERISTICS (CONTINUED)


9. Ripple Rejection vs Frequency



$V_o=0.9V, V_{in}=2.5V, V_{pp}=1V$




$V_o=1.5V, V_{in}=2.5V, V_{pp}=1V$




$V_o=2.5V, V_{in}=3.3V, V_{pp}=0.3V$


10. Load Transient Response




$V_o=1.5V, V_{in}=3.3V, I_o=10mA \text{ to } 1.5A$



$V_o=1.5V, I_o=10mA \text{ to } 500mA$




11. Line Transient Response



$V_o=1.5V, V_{in}=2V \text{ to } 3.3V, I_o=1mA$



■ ORDERING INFORMATION



■ MARKING INFORMATION


(1) TO252

(2) TO263






■ PACKAGE INFORMATION

(1) TO252



| Symbol | Dimensions In Millimeters | | | Dimensions In Inches | | |
|--------|---------------------------|------|------|----------------------|-------|-------|
| | Min. | Nom. | Max. | Min. | Nom. | Max. |
| A | 6.40 | 6.60 | 6.80 | 0.256 | 0.264 | 0.272 |
| B | 5.20 | 5.35 | 5.50 | 0.208 | 0.214 | 0.220 |
| C | 6.80 | 7.00 | 7.20 | 0.272 | 0.280 | 0.288 |
| D | 2.20 | 2.50 | 2.80 | 0.088 | 0.100 | 0.112 |
| E | 2.30REF | | | 0.092REF | | |
| F | 0.70 | 0.80 | 0.90 | 0.028 | 0.032 | 0.036 |
| S | 0.60 | 0.75 | 0.90 | 0.024 | 0.030 | 0.036 |
| G | 0.50 | 0.60 | 0.70 | 0.020 | 0.024 | 0.028 |
| H | 2.20 | 2.30 | 2.40 | 0.088 | 0.092 | 0.096 |
| J | 0.45 | 0.50 | 0.55 | 0.018 | 0.020 | 0.022 |
| K | 0 | 0.07 | 0.15 | 0 | 0.003 | 0.006 |
| L | 0.90 | 1.20 | 1.50 | 0.036 | 0.048 | 0.060 |
| M | 5.40 | 5.60 | 5.80 | 0.216 | 0.224 | 0.232 |
| R | 0.80 | 1.00 | 1.20 | 0.032 | 0.040 | 0.048 |

2) TO263



| Symbol | Dimensions In Millimeters | | | Dimensions In Inches | | |
|--------|---------------------------|-------|-------|----------------------|-------|-------|
| | Min. | Nom. | Max. | Min. | Nom. | Max. |
| A | 4.07 | 4.46 | 4.85 | 0.163 | 0.176 | 0.194 |
| B | 0.51 | 0.84 | 1.02 | 0.020 | 0.033 | 0.041 |
| C | 0.36 | 0.50 | 0.74 | 0.014 | 0.020 | 0.030 |
| C2 | 1.14 | 1.27 | 1.65 | 0.046 | 0.050 | 0.066 |
| D | 8.20 | 9.15 | 9.65 | 0.328 | 0.360 | 0.380 |
| E | 9.65 | 10.16 | 10.67 | 0.386 | 0.400 | 0.427 |
| e | 1.57 | 1.71 | 1.85 | 0.063 | 0.068 | 0.074 |
| L | 14.45 | 15.24 | 15.88 | 0.578 | 0.600 | 0.635 |
| L1 | 1.78 | 2.54 | 2.79 | 0.071 | 0.100 | 0.110 |
| L2 | | | 2.92 | | | 0.115 |

